

SQUARE Channel

Specification Sheet

SQUARE Channel

SQUARE Sturdy profile with many mounting options.

Date

Project Notes



FEATURES

- · Industrial extrusions for custom lighting
- In-house and field cuttable channels to work with individual specifications
- Channels act as a heat sink, cooling and prolonging the LED tape light lifespan
- Multiple finishes and hardware available
- Provides additional defense from dust and debris, protecting the LED investment
- 5-Year Warranty



ORDERING CODES

Order channels, and components for field assembly

Diode LED	Model	Series	Lens		Length		
DI							
	СРСНВ	SQ	CLT (Architectural Clear Lens) BL (Black Lens)	*blank* (Frosted Lens) PD (Premium Diffusion Lens)	48 (48 in. aluminum) 48B (48 in. black) 48W (48 in. white)	96 (96 in. aluminum) 96B (96 in. black) 96W (96 in. white)	

RECOMMENDED TAPE LIGHTS

Inquire for Tape Lights not listed

- Blaze
 Blaze Colors
 Blaze Mini
 Blaze Wet Location

- Blaze X
 Blaze X Wet Location
 Dazzle RGB

- Dazzle RGBW
 Dazzle RGBW 4D
 Streamlite
 Streamlite Tunable White
- Valent
 Valent Tunable White
 Valent X

CHANNEL SPECIFICATIONS

MODEL	DIAGRAM	INCLUDED ACCESSORIES	CONNECTION OPTIONS	TECHNICAL RATINGS	MOUNTING OPTIONS WITH DIMENSIONS			
SQUARE Channel DI-CPCHB-SQ	Height (H): 0.55 in. Width (W): 0.82 in. Interior Depth (ID): 0.27 in. Interior Width (IW): 0.67 in.	48" Aluminum Channel 48 in. channel & frosted cover Mounting hardware End caps: Tx open, 1x closed. 48" Black & White Channels 48" Black & White Channels 48" Black & White Channels 48 un channel & clear, or frosted lens 4x surface mounted clips 2x End-to-end interconnects 96" Aluminum Channel 96 in. channel & frostedcover Mounting hardware End caps: 2x open, 2x closed. 96" Black & White Channels 96" Black & White Channels 4x surface mounted clips 4x surface mounted clips 2x End-to-end interconnects	8mm Tape Light w/Terminal Block 8mm Tape Light w/Soldered Lead 12mm Tape Light w/Terminal Block 12mm Tape Light w/Soldered Lead	Premium Diffusion Lens • Light Loss: 10% • CCT Shift: -30K • IP Rating Shift: IP40	Chromapath Surface Mount: 0.61 × 0.82 in. (H x W) Premium Diffusion: 1.13 × 0.82 in. (H x W)	Vertical Mount: 0.61 × 0.82 in. (H x W)	Rotating Mount: 1.29 × 0.82 in. (H x W)	Hanging Mount: 1.51 × 0.82 in. (H x W)

DIFFUSION KEY

Runway Diffusion			Semi-Diffused			Dotless		
Architectural Frosted Lens	Black Lens	Premium Diffusion Lens	Architectural Frosted Lens	Black Lens	Premium Diffusion Lens	Architectural Frosted Lens	Black Lens	Premium Diffusion Lens
BLAZE" - BLBSC1 - BLAZE" - BLBSC2 - BLAZE" - BLBSC2 - BLAZE" - BLSC2 - BLAZE" - BLX - BLAZE - BLX - BLAZE - BLX -	- BLAZET - BLBSC1 - BLAZET - BLBSC2 - BLAZET - BLBSC3 - BLAZET X - BLX1 - BLAZET X - BLX1 - BLAZET X - BLX1 - BLAZET M - BLX1 - BLXZET M - BLX1 - BLXZET M - BLXXET M	None	Chazzie RGB VALENTE Tembels Wate VALENTE TEMBEL THE TEMBEL THE TEMBEL CANDIDATE BLAZE** SWEL Coartion - BLX2 BLAZE** Wet Location - BLX2 BLAZE** Wet Location - BLXC3 BLAZE** Wet Location - BL	Dazzie RGB VALENTE - Trauble White VALENTE - Trauble White VALENTE -	BLAZE" X Wet Location - BLX1 BLAZE" Wet Location - BLBSC1	- STREAMLITE" - STMLT - STMEAMLITE - STMLT - STMEAMLITE - STMLT - VALENTS - VL2 - VALENTS - VL5 - VL5 - VALENTS - VL5 -	- STBEAMLITE - STMLT - STREAMLITE - STMLT - STREAMLITE - STMLT - STMLT - STMLT - VALENTS - VIS - VALENTS - VIS	### #### #############################



SQUARE Channel

Specification Sheet

SQUARE Channel

SQUARE Sturdy profile with many mounting options.

	https://www.diodeled.com/square-channel.html	间数表面
Date		家服 多硬
		ALC: N
Project Notes		

CERTIFICATIONS

Safety

Meets the following certifications when installed with compatible UL Listed tape light:

- UL Listed 2108. UL 1598 / CSA 250.0-08, UL 8750. UL 879 / CAN/ CSA-C22.2 no. 207-M89. E469769 (UL Listed), E469770.
- Approved for storage areas of clothes closets per NEC 410.16.A.3 and 410.16.C.5

Environmental

Suitable for indoor, dry, damp, and wet location use

Safety / Warnings / Disclosures

- 1. Install in accordance with national and local electrical code regulations
- 2. This product is intended to be installed and serviced by a qualified, licensed electrician
- Ensure applicable wire is installed between driver, fixture, and any controls in-between. When choosing wire, 3. factor in voltage drop, amperage rating, and type (in-wall rated, wet location rated, etc.). Inadequate wire installation could overheat wires, and cause fire.
- 4. Do not install in environment where LED chips are exposed to direct sunlight as damage to the phosphor will occur.
- 5. Do not install in environment where excessive heat may exist (ex. close proximity to fireplace, etc.) See Ambient
- 6. Do not install indoor LED tape light products in outdoor / wet location environments. Only wet location tape light models are rated for outdoor / wet locations.
- 7. Do not modify product beyond instructions or warranty will be void.
- 8. Tape light must be handled with care. Excessive handling, bending, and pressure may damage the product, voiding the warranty.
- Actual color may vary from what is pictured on this sheet and other print materials due to the limitations of photographic processes.
- We reserve the right to modify and improve the design of our fixtures without prior notice. We cannot guarantee to

 10. match existing installed fixtures for subsequent orders or replacements in regards to product appearance, CCT, or lumen output.

WARRANTY

Limited Warranty

5 Years

This warranty does not include the additional accessories referenced in this specification sheet. Complete warranty details for fixtures and additional accessories are available at www.diodeled. com/limited-warranty/ within the Policies section. For warranty related questions please contact product support.

Consumer's Acknowledgment

Elemental LED, Inc. stands behind its products when they are used properly and according to our specifications. By purchasing our products, the purchaser agrees and acknowledges that lighting design, configuration and installation is a complex process, wherein seemingly minor factors or changes in layout and infield adjustments can have a significant impact on an entire system. Choosing the correct components is essential. Elemental LED is able to work with the original purchaser to make an appropriate product selection to the extent of the limited information that the customer can provide, but it is virtually impossible for Elemental LED to design a system that foresees every unknown factor. For this reason, this Warranty does not cover problems caused by improper design, configuration or installation issues. Any statement from a Elemental LED employee or agent regarding a customer's bill of goods and/or purchase order is NOT an acknowledgment that the products purchased are designed and configured correctly. The purchase agrees and acknowledges that it is the customer's responsibility to adhere strictly to all information contained in the Product Specification Sheets.

There is often more than one way to design, configure and layout an LED lighting application properly to achieve the same lighting effect. Elemental LED strongly recommends that licensed professionals be used in the design and installation of lighting systems that include Elemental LED products. The specifications include important information that a designer and installer should carefully review and strictly follow. Qualified designers and certified and/or licensed installers, with access to the final installation environment, customer goals, and Elemental LED product specifications can make the requisite decisions appropriate for a successful finished lighting application.