



Item#: **82233**
EMERGENCY BACKUP
FLUORESCENT FIXTURES

FEATURES

- Works with AC ballast to provide normal light when there is a power failure.
- Operates one or two lamps in the emergency mode for a minimum of 90 minutes.
- LED indicator light and test switch.
- Compact design fits most fluorescent fixtures.

LAMP COMPATIBILITY

Operates one or two lamps:

1 Lamp - 1300 Lumens 2'-8' single, T8, T10, T12, Circular or U-Bend, Rapid or Instant Start.

2 Lamps - 650 Lumens 2'-4' single, T8, T10, T12, Circular or U-Bend, Rapid or Instant Start.

SUPPORTING DOCUMENTS (Grey = not available at this time.)

Product Sheet	VIEW
Install Instructions	VIEW

PACKAGING	UPC	DIMENSIONS (LxWxH)	GROSS WEIGHT (Lbs)	
Master Carton	10	--	14.6" x 11.4" x 8.7"	30.9
Individual Box	1	--	--	3.1
Country of Origin	China			
HS Tariff	9405.10.8020			

ORDERING

ITEM#	DESCRIPTION	CASE
82233	EMERGENCY BACKUP 1300 LUMENS 1 OR 2 LAMP 2ft - 8ft T8/T10/T12/U-BEND/CIRCLINE	10

ELECTRICAL

Voltage	120/277V
---------	----------

PERFORMANCE

Max. Lumen Output	1300
Emergency Time	Minimum 90 Min.
Recharge Time Required	24 Hrs
Battery Type	Rechargeable Sealed NiCd

CONSTRUCTION

Housing	Steel
Finish	White

DIMENSIONS (Inches)

Length	13.4"
Width	2.4"
Height	1.5"
Net Weight (Lbs)	--

Specifications are subject to change without notice.

